

Exam in TSKS01 Digital Communication

- Exam code:** TEN1
- Date:** 2019-08-24 **Time:** 08:00–12:00
- Place:** TER2
- Teacher:** Özlem Tugfe Demir, tel: 013 - 28 13 17, is visiting the exam. The examiner is Emil Björnson, tel: 0709 - 49 49 24.
- Visiting exam:** Around 9:30
- Administrator:** Carina Lindström, 013 - 28 44 23, carina.e.lindstrom@liu.se
- Department:** ISY
- Allowed aids:** Pocket calculator with empty memory.
Olofsson: Tables and Formulas for Signal Theory.
- Number of tasks:** 7
- Solutions:** Will be published within one week after the exam at <http://www.commsys.isy.liu.se/TSKS01>
- Result:** You get a message about your result via an automatic email from Ladok. Note that we cannot file your result if you are not registered on the course. That also means that you will not get an automated email about your result if you are not registered on the course.
- Exam return:** 2019-09-12, 12:45–13:10, Emil Björnson's office, Building B, top floor, corridor A between entrances 27–29. After that in the student office of Dept. of EE. (ISY), Building B, Corridor D, between Entrances 27–29, right next to Café Java.
- Important:** **Solutions and answers must be given in English.**

Grading: This exam consists of three parts: an introductory task, a question part, and a problem-solving part. The introductory task consists of two rather simple subtasks that test the ability to perform standard calculations. Each task in the question part and the problem-solving part can give the number of points indicated in the margin. The question part can give you at most 10 points and the problem-solving part can give you at most 20 points. For passing the exam, you need

- at least one of the two subtasks of the introductory task solved correctly,
- at least 3 points from the question part,
- at least 6 points from the problem-solving part,
- and totally at least 14 points.

Grade limits:


- Grade three (ECTS C): 14 points,
- Grade four (ECTS B): 19 points,
- Grade five (ECTS A): 24 points.

Sloppy solutions and solutions that are hard to read are subject to hard judgement, as are unreasonable answers.

Introductory task

1 This task has to be solved correctly as partial fulfillment for passing the exam.

a. A binary modulation scheme uses the following two signal points:



Determine the error probability if we communicate over an AWGN channel where the noise has power spectral density $N_0/2 = 0.5$. The receiver uses an ML detector.

b. Consider a linear code for error control with generator matrix

$$G = \begin{pmatrix} 1 & 0 & 1 & 1 & 0 \\ 0 & 1 & 0 & 1 & 1 \end{pmatrix}.$$

Compute all the codewords.

Question part

2 Explain how syndrome decoding works. Make sure to provide both a general description with arbitrary matrices (remember to define their dimensions!) and an example with numbers in the matrices. Explain why syndrome decoding leads to an ML detector. (5 p)

- 3 Are the following claims true or false? You do not need to explain your answers. (5p)
- a. The symbol error probability is always larger or equal to the bit error probability.
 - b. Every linear block code contains a codeword with only zeros.
 - c. The rate of a linear block code is always greater or equal to one.
 - d. An eye pattern can be affected by the choice of basis function.
 - e. The amplitude of the signal carries the information in PSK.

For each of the claims above, a correct answer gives you +1 point, while an incorrect answer gives you -1 point. No answer give you 0 points for that claim, so a good strategy is to only give an answer if you are sure that it is correct. You cannot get less than 0 points totally from this task.

Problem-solving part

- 4 Determine the relation between *bit-error probability* and *symbol-error probability* for (5 p)
- a. 16-PSK,
 - b. 16-FSK.

In both cases consider the best mapping of bits on signals for that particular constellation. If needed, you are allowed to use the nearest-neighbour approximation.

- 5 We want to send the message $m(x) = x^5 + x^2 + x$ using a CRC code defined by the CRC polynomial $p(x) = x^4 + x^3 + x + 1$. (5p)
- a. Draw a linear feedback shift register for CRC code generation. (2p)
 - b. Which codeword $c(x)$ corresponds to $m(x)$? (3p)

- 6** Consider a Hamming-[7, 4] code. Now, create a new code by appending an extra bit to all codewords. This extra bit is the sum of all bits in the original codeword. Determine the length, dimension, minimum distance and size of the resulting code. (5 p)
- 7** We need to design a communication system for transmitting packets of 11 bits of information over an AWGN channel. The communication system will operate in a consumer environment where the packet error probability must be below 0.05. (5p)
- Suppose we send the packet using BPSK modulation without error control coding. How large must the SNR E_b/N_0 be to satisfy the requirements?
 - We want to improve the system by using the binary Hamming-[15,11] code. How many errors can this code correct?
 - Suppose we use the code from Part b together with BPSK modulation. Derive an expression for the packet error probability in this case.
 - What is the packet error probability with the Hamming-[15,11] code if E_b/N_0 has the same value as in Part a?

The *Q*-function, table of $Q(x) = \int_x^\infty \frac{1}{\sqrt{2\pi}} e^{-t^2/2} dt$ for $0.00 \leq x \leq 5.99$.

<i>x</i>	0	1	2	3	4	5	6	7	8	9	exp
0.0	5.0000	4.9601	4.9202	4.8803	4.8405	4.8006	4.7608	4.7210	4.6812	4.6414	
0.1	4.6017	4.5620	4.5224	4.4828	4.4433	4.4038	4.3644	4.3251	4.2858	4.2465	
0.2	4.2074	4.1683	4.1294	4.0905	4.0517	4.0129	3.9743	3.9358	3.8974	3.8591	
0.3	3.8209	3.7828	3.7448	3.7070	3.6693	3.6317	3.5942	3.5569	3.5197	3.4827	
0.4	3.4458	3.4090	3.3724	3.3360	3.2997	3.2636	3.2276	3.1918	3.1561	3.1207	
0.5	3.0854	3.0503	3.0153	2.9806	2.9460	2.9116	2.8774	2.8434	2.8096	2.7760	
0.6	2.7425	2.7093	2.6763	2.6435	2.6109	2.5785	2.5463	2.5143	2.4825	2.4510	-1
0.7	2.4196	2.3885	2.3576	2.3270	2.2965	2.2663	2.2363	2.2065	2.1770	2.1476	
0.8	2.1186	2.0897	2.0611	2.0327	2.0045	1.9766	1.9489	1.9215	1.8943	1.8673	
0.9	1.8406	1.8141	1.7879	1.7619	1.7361	1.7106	1.6853	1.6602	1.6354	1.6109	
1.0	1.5866	1.5625	1.5386	1.5151	1.4917	1.4686	1.4457	1.4231	1.4007	1.3786	
1.1	1.3567	1.3350	1.3136	1.2924	1.2714	1.2507	1.2302	1.2100	1.1900	1.1702	
1.2	1.1507	1.1314	1.1123	1.0935	1.0749	1.0565	1.0383	1.0204	1.0027	9.8525	
1.3	9.6800	9.5098	9.3418	9.1759	9.0123	8.8508	8.6915	8.5343	8.3793	8.2264	
1.4	8.0757	7.9270	7.7804	7.6359	7.4934	7.3529	7.2145	7.0781	6.9437	6.8112	
1.5	6.6807	6.5522	6.4255	6.3008	6.1780	6.0571	5.9380	5.8208	5.7053	5.5917	
1.6	5.4799	5.3699	5.2616	5.1551	5.0503	4.9471	4.8457	4.7460	4.6479	4.5514	
1.7	4.4565	4.3633	4.2716	4.1815	4.0930	4.0059	3.9204	3.8364	3.7538	3.6727	-2
1.8	3.5930	3.5148	3.4380	3.3625	3.2884	3.2157	3.1443	3.0742	3.0054	2.9379	
1.9	2.8717	2.8067	2.7429	2.6803	2.6190	2.5588	2.4998	2.4419	2.3852	2.3295	
2.0	2.2750	2.2216	2.1692	2.1178	2.0675	2.0182	1.9699	1.9226	1.8763	1.8309	
2.1	1.7864	1.7429	1.7003	1.6586	1.6177	1.5778	1.5386	1.5003	1.4629	1.4262	
2.2	1.3903	1.3553	1.3209	1.2874	1.2545	1.2224	1.1911	1.1604	1.1304	1.1011	
2.3	1.0724	1.0444	1.0170	9.9031	9.6419	9.3867	9.1375	8.8940	8.6563	8.4242	
2.4	8.1975	7.9763	7.7603	7.5494	7.3436	7.1428	6.9469	6.7557	6.5691	6.3872	
2.5	6.2097	6.0366	5.8677	5.7031	5.5426	5.3861	5.2336	5.0849	4.9400	4.7988	
2.6	4.6612	4.5271	4.3965	4.2692	4.1453	4.0246	3.9070	3.7926	3.6811	3.5726	
2.7	3.4670	3.3642	3.2641	3.1667	3.0720	2.9798	2.8901	2.8028	2.7179	2.6354	-3
2.8	2.5551	2.4771	2.4012	2.3274	2.2557	2.1860	2.1182	2.0524	1.9884	1.9262	
2.9	1.8658	1.8071	1.7502	1.6948	1.6411	1.5889	1.5382	1.4890	1.4412	1.3949	
3.0	1.3499	1.3062	1.2639	1.2228	1.1829	1.1442	1.1067	1.0703	1.0350	1.0008	
3.1	9.6760	9.3544	9.0426	8.7403	8.4474	8.1635	7.8885	7.6219	7.3638	7.1136	
3.2	6.8714	6.6367	6.4095	6.1895	5.9765	5.7703	5.5706	5.3774	5.1904	5.0094	
3.3	4.8342	4.6648	4.5009	4.3423	4.1889	4.0406	3.8971	3.7584	3.6243	3.4946	
3.4	3.3693	3.2481	3.1311	3.0179	2.9086	2.8029	2.7009	2.6023	2.5071	2.4151	-4
3.5	2.3263	2.2405	2.1577	2.0778	2.0006	1.9262	1.8543	1.7849	1.7180	1.6534	
3.6	1.5911	1.5310	1.4730	1.4171	1.3632	1.3112	1.2611	1.2128	1.1662	1.1213	
3.7	1.0780	1.0363	9.9611	9.5740	9.2010	8.8417	8.4957	8.1624	7.8414	7.5324	
3.8	7.2348	6.9483	6.6726	6.4072	6.1517	5.9059	5.6694	5.4418	5.2228	5.0122	
3.9	4.8096	4.6148	4.4274	4.2473	4.0741	3.9076	3.7475	3.5936	3.4458	3.3037	-5
4.0	3.1671	3.0359	2.9099	2.7888	2.6726	2.5609	2.4536	2.3507	2.2518	2.1569	
4.1	2.0658	1.9783	1.8944	1.8138	1.7365	1.6624	1.5912	1.5230	1.4575	1.3948	
4.2	1.3346	1.2769	1.2215	1.1685	1.1176	1.0689	1.0221	9.7736	9.3447	8.9337	
4.3	8.5399	8.1627	7.8015	7.4555	7.1241	6.8069	6.5031	6.2123	5.9340	5.6675	
4.4	5.4125	5.1685	4.9350	4.7117	4.4979	4.2935	4.0980	3.9110	3.7322	3.5612	-6
4.5	3.3977	3.2414	3.0920	2.9492	2.8127	2.6823	2.5577	2.4386	2.3249	2.2162	
4.6	2.1125	2.0133	1.9187	1.8283	1.7420	1.6597	1.5810	1.5060	1.4344	1.3660	
4.7	1.3008	1.2386	1.1792	1.1226	1.0686	1.0171	9.6796	9.2113	8.7648	8.3391	
4.8	7.9333	7.5465	7.1779	6.8267	6.4920	6.1731	5.8693	5.5799	5.3043	5.0418	
4.9	4.7918	4.5538	4.3272	4.1115	3.9061	3.7107	3.5247	3.3476	3.1792	3.0190	-7
5.0	2.8665	2.7215	2.5836	2.4524	2.3277	2.2091	2.0963	1.9891	1.8872	1.7903	
5.1	1.6983	1.6108	1.5277	1.4487	1.3737	1.3024	1.2347	1.1705	1.1094	1.0515	
5.2	9.9644	9.4420	8.9462	8.4755	8.0288	7.6050	7.2028	6.8212	6.4592	6.1158	
5.3	5.7901	5.4813	5.1884	4.9106	4.6473	4.3977	4.1611	3.9368	3.7243	3.5229	
5.4	3.3320	3.1512	2.9800	2.8177	2.6640	2.5185	2.3807	2.2502	2.1266	2.0097	-8
5.5	1.8990	1.7942	1.6950	1.6012	1.5124	1.4283	1.3489	1.2737	1.2026	1.1353	
5.6	1.0718	1.0116	9.5479	9.0105	8.5025	8.0224	7.5686	7.1399	6.7347	6.3520	
5.7	5.9904	5.6488	5.3262	5.0215	4.7338	4.4622	4.2057	3.9636	3.7350	3.5193	
5.8	3.3157	3.1236	2.9424	2.7714	2.6100	2.4579	2.3143	2.1790	2.0513	1.9310	-9
5.9	1.8175	1.7105	1.6097	1.5147	1.4251	1.3407	1.2612	1.1863	1.1157	1.0492	

For $x > 0$, we have $(1 - x^{-2}) \frac{1}{x\sqrt{2\pi}} e^{-x^2/2} dt < Q(x) < \frac{1}{x\sqrt{2\pi}} e^{-x^2/2} dt$. For large x we have $Q(x) \approx \frac{1}{x\sqrt{2\pi}} e^{-x^2/2} dt$.